74 mm

54 mm


气传导运动蓝牙耳机



使用指南及保修说明

Operating instructiong and Warranty description

示意图及配件



① Type-C充电口　② 指示灯/麦克风　③ “+” 键

④ “-” 键　⑤ On/Off功能键　⑥ TF插卡槽

配件清单

1. 蓝牙耳机
2. TYPE-C充电线
3. 说明书(含保修卡)

使用说明

开机

长按开机按键3秒，当指示灯红蓝交替闪烁并伴随“开机”提示音（英文模式：“Power On”），表示耳机已经开机。

蓝牙连接

首次使用，耳机正常开机后，红蓝交替闪烁会进入蓝牙配对状态，进入手机设置，打开蓝牙搜索“G1”，点击配对，连接成功后提灯熄灭。

更换配对设备及回连

断开当前配对设备蓝牙，耳机指示灯红蓝交替闪烁，其他设备即可搜索到“G1”，点击连接配对。

耳机支持自动回连，可自动回连已配对的设备，正常开机后即会自动回连最后一次连接的设备，请确保连接设备蓝牙已开启

关机

长按关机按键3秒即会关机并伴随“关机”提示音（英文模式提示：Power Off），指示灯熄灭。

充电

当电量低于10%时或提示电量低，即表示需要充电，插入充电线红灯常亮表示正在充电。

多设备连接

支持多设备连接蓝牙耳机。搜索蓝牙设备名“G1”,点击配对，连接上第一部设备。关闭第一部设备蓝牙，耳机重新进入配对状态，在第二部蓝牙设备搜索设备名“G1”，点击配对。再打开刚才第一个设备蓝牙，耳机会自动连接第一部设备（或在第一部设备点击“G1”蓝牙名进行回连）

中英文切换

默认为英文；可在未连接状态双击开机键切换“中文/英文”提示音

长按3秒“开关键”----- 耳机开关机

短按“开关键” ----- 暂停
短按“开关键” ----- 播放
长按“-”键1秒 ------ 音量减
长按“+”键1秒 ------ 音量加
短按“+”键 ----- 下一曲
短按“-”键 ----- 上一曲

来电状态

短按 “开关键” ----- 接听
短按 “开关键” ----- 挂断
长按 “开关键”1.5秒 ----- 拒接

切换TF卡与蓝牙模式

插入TF卡自动切换为TF卡模式
拔出TF卡自动切换为蓝牙模式

产品参数

- 型号：G1
- 版本：5.2
- 重量：21g
- 电池：80 mAh
- 充电：约2小时
- 播放：约4小时
- 通话：约4小时
- 防水：IPX45
- 距离：蓝牙10米
- 输入：5V/100 mA
- 协议：A2DP, AVRCP, HSP, HFP

故障及排除

无法开机

确定耳机是否充满电量，按键是否误操作，同时充电激活。

无法蓝牙连接

检查是否已被其它设备连接耳机。
耳机指示灯是否处于红蓝交替闪烁阶段。

无法回连

确定当前（如手机蓝牙）是否正常开启。

耳机音量较小

手机是否加大音量，需要手机增加或减小音量. 佩戴方式是否正确.

合格证
Q. C. Passed

产品保修卡

该卡为产品保修凭证,请妥善保管

	产品型号:
	客户名称:

产品维修记录

	不良现象	

Air conduction motion Bluetooth earphones


USER MANUAL



Instructions for usage and warranty

Operating instructiong and Warranty description

Schematic and Accessories



① Type-C charging port　② Indicator light/Microphone

③ “+”key　④ “-”key　⑤ On/Off multifunction key

⑥ TFcard slot

Packing List

1. Bone Conduction Bluetooth Air Conduction
2. TYPE-C charging cable
3. User manual

Instructions for use

Power On

Long Press On the Power button for 3 seconds, when the indicator flashes red and blue alternately and accompanied by a"Power On" sound (English mode: "Power On") , indicating that the headset has been turned On.

Bluetooth Connection

For the first use, atfer the headset is turned on normally,it twill enter the Bluetooth pairing state. At this, you can search for "G1" in the Bluetooth settings ofthe mobile phone. After clicking the connection is succrssful , the indicator light will turn off , and the blueilght will flash once.

Change paired device and connect back

Disconnect the Bluetooth of the current pairing device. The headphone indicator flashes red and blue alternately. Other devices can search for"G1" and click connect to pair. The headset supports automatic reconnect, which can automatically reconnect the paired device. After the normal boot, it will automatically reconnect the last connected device. Please make sure the connected device Bluetooth is turned on

Power Off

When the power is less than 10% or low power, that is, the need to charge, plug in the charging line red light often light that is charging.

Charge

Support multi-device Bluetooth headset connection. Search for the Bluetooth device name "G1", and click on match to connect to the first device. Turn off the Bluetooth on the first device, put the headset back into pairing mode, search for the device name "G1" on the second device, and click pairing. Turn on the Bluetooth on the first device, and the headset will automatically connect to the first device (or click the "G1" Bluetooth name on the first device to reconnect) so that you can connect to the device.

Switch Between Chinese and English

The default is English; You can double-click the power button in the disconnected state to switch to the Chinese/English prompt tone

Press the “On” button for 3 seconds

Short press “Power On/Off” -----Pause
Short press “Power On/off” ------Play
Press the “+” button for 1 second -----Volume duwn
Press the “+” button for 1 second ----- Volume up

Press “+key” ----- Next song
Press “-key” ----- Last song

Call status

Short press “Power On/Off” ------ Answer it
Short press “Power on/Off” ----- Hang up
Press and hold on for 1.5 seconds----- Reject

Switch TF card to Bluetooth mode

The TF card automatically switches to TF card mode
Automatically switch to Bluetooth mode when TF card is removed

Product parameters

- Model : G1
- Bluetooth version: 5.2
- Weight: 21g
- Battery: 80 mAh
- Charging time: about 2 hours
- Playing time: About 4 hours
- Talk: About 4 hours.
- Waterproof: IPX45
- Bluetooth connection distance: 10 m
- Input: 5V /100mA
- Protocol: A2DP,AVRCP , HSP , HFP

Troubleshooting

Can not boot

Determine whether the headset is fully charged and whether the key is misoperated,and charge it to activate the headset.

No Bluetooth connection

Whether the headphone indicator blinks alternately red and blue

Unable to automatically reconnect

Determine whether the front end (such as mobile phone Bluetooth) is enabled properly.

Low volume of headphones

Whether the volume of the phone is increased, and whether the wearing mode is correct

Certificate of approval
Q. C. Passed

Product warranty card

This card is a product warranty certificate, please keep

oduct name:	Product model:
urchase date:	Client's name:
Contact	

Product maintenance records

The date of	Bad phenomenon	Solution